

This document compiles reference values only. Actual performance in a live streaming environment depends on individual IP camera settings and/or network conditions. If the resulting video stream performance is unsatisfactory, try setting the IP camera to a lower resolution or bit rate. In this case, refer to the IP camera's manual or contact the manufacturer.

DuraVision DX0211-IP

IP Decoding Box

Output Video: 1920 × 1080 at 60 fps

Video Codec: H.264 (when bit rate is set to 4096 kbps)

1 Channel	3840 × 2160 / 30 fps
4 Channels	3840 × 2160 / 20 fps
9 Channels	1920 × 1080 / 30 fps
16 Channels	1920 × 1080 / 20 fps
32 Channels	1280 × 720 / 15 fps

Video Codec: MJPEG

1 - 32 Channels 640 × 480 / 30 fps

Output Video: 3840 × 2160 at 60 fps

Video Codec: H.264 (when bit rate is set to 4096 kbps)

1 Channel	3840 × 2160 / 30 fps
4 Channels	3840 × 2160 / 20 fps
9 Channels	1920 × 1080 / 25 fps
16 Channels	1920 × 1080 / 20 fps
32 Channels	1280 × 720 / 15 fps

Video Codec: MJPEG

1 - 32 Channels 640 × 480 / 30 fps

DuraVision FDF2304W-IP / FDF4627W-IP

23" IP Decoding Monitor

Output Video: 1920 × 1080 at 60 fps

Video Codec: H.264 (when bit rate is set to 4096 kbps)

1 Channel	1920 × 1080 / 30 fps
4 Channels	1920 × 1080 / 20 fps
9 Channels	1280 × 720 / 20 fps
16 Channels	640 × 480 / 30 fps

Video Codec: MJPEG

1 - 16 Channels 640 × 480 / 30 fps